



Piriç-R-erkek dişli E-Adaptör için W/P-TW enjeksiyon kalıplı Elektrofüzyon PE 100-RC siyah

Boyut	Kod	Detay	Ağırlık	da(OD) mm	s mm	L mm	L1 mm	L2 mm
20 X 1/2	70.181.0020.11	20X1/2" SDR 11 PN16	0.103	20	3	81	40	16
25 X 3/4	70.181.0025.11	25X3/4" SDR 11 PN16	0.133	25	3	85	43	16
32 X 1/2	70.181.2032.11	32X1/2" SDR 11 PN16	0.195	32	3	88	46	16,5
32 X 3/4	70.181.2532.11	32X3/4" SDR 11 PN16	0.185	32	3	90	46	18
32 X 1	70.181.0032.11	32X1" SDR 11 PN16	0.181	32	3	92	46	19
32 X 1 1/4	70.181.4032.11	32X1 1/4" SDR 11 PN16	0.300	32	3	95	46	23
32 X 1 1/2	70.181.5032.11	32X1 1/2" SDR 11 PN16	0.480	32	3	97	46	25
40 X 1	70.181.3240.11	40X1" SDR 11 PN16	0.290	40	3,7	99	51	21
40 X 1 1/4	70.181.0040.11	40X1 1/4" SDR 17-11 PN16	0.269	40	3,7	100	51	21
40 X 1 1/2	70.181.5040.11	40X1 1/2" SDR 17-11 PN16	0.400	40	3,7	103	51	25
40 X 2	70.181.6340.11	40X2" SDR 11 PN16	0.760	40	3,7	107	51	29



Boyut	Kod	Detay	Ağırlık	da(OD) mm	s mm	L mm	L1 mm	L2 mm
50 X 1	70.181.3250.11	50X1" SDR 11 PN16	0.440	50	4,6	105	57	21
50 X 1 1/4	70.181.4050.11	50X1 1/4" SDR 11 PN16	0.415	50	4,6	107	57	22
50 X 1 1/2	70.181.0050.11	50X1 1/2" SDR 17-11 PN16	0.380	50	4,6	109	57	24,8
50 X 2	70.181.6350.11	50X2" SDR 11 PN16	0.680	50	4,6	114	57	29
63 X 1 1/4	70.181.4063.11	63X1 1/4" SDR 11 PN16	0.634	63	5,8	117	65	21
63 X 1 1/2	70.181.5063.11	63X1 1/2" SDR 11 PN16	0.570	63	5,8	121	65	25
63 X 2	70.181.0063.11	63X2" SDR 17-11 PN16	0.573	63	5,8	124	65	27